

# Low Phase Noise Crystal Oscillators data 3.2 × 2.5 SPXO CMOS

Vdd: 3.3 V  
 Output Level: CMOS  
 Size: 3225

Agilent: E5052B (Signal Source Analyzer)  
 RMS Jitter: 10Hz~5MHz  
 Model: KCO-338BR-IW-24.576MHz

	RMS Jitter (fs/typ)	Phase Noise ( dBc/Hz )						
		10Hz	100Hz	1kHz	10kHz	100kHz	1MHz	5MHz
標準品タイプ	334.142	-72.739	-104.952	-130.491	-144.491	-150.123	-154.301	-160.217
低位相タイプ	112.506	-103.504	-131.096	-145.428	-156.777	-162.726	-165.320	-165.386

